

Lead Forming Lamps

Line No.	Volts	Amps	M.S.C.P	Filament Type	Life Hours
1	2.5	0.350	0.600	C-2R	30
2	5.0	0.020	0.020	C-2R	10,000
3	5.0	0.021	0.034	C-2R	10,000
4	5.0	0.060	0.030	C-2R	100,000
4	5.0	0.060	0.050	C-2R	60,000
5	5.0	0.060	0.150	C-2R	5,000
6	5.0	0.075	0.090	C-2R	25,000
7	5.0	0.115	0.150	C-2R	40,000
8	5.0	0.115	0.150	CC-6	40,000
9	6.0	0.200	0.600	C-2R	2,000
10	6.3	0.200	0.550	C-2R	5,000
11	10.0	0.095	0.220	C-2F	4,000
12	12.0	0.040	0.150	C-2F	10,000
13	12.0	0.060	0.150	C-2F	16,000
14	14.0	0.040	0.120	C-2F	10,000
15	14.0	0.060	0.200	C-2F	10,000
16	14.0	0.065	0.150	C-2F	16,000
17	14.0	0.070	0.200	C-2F	10,000
18	14.0	0.080	0.300	C-2F	25,000
19	14.0	0.080	0.500	C-2F	1,500
20	14.0	0.100	0.500	C-2F	10,000
21	14.0	0.125	0.700	C-2V	10,000
22	14.0	0.135	0.800	C-2V	10,000
23	14.0	0.135	0.800	C-2V	10,000
24	28.0	0.024	0.150	CC-2F	16,000
25	28.0	0.040	0.200	C-2F	10,000
26	28.0	0.040	0.300	C-2F	10,000
27	48.0	0.025	0.200	CC-2F	5,000
28	60.0	0.020	0.150	CC-2F	5,000